

MTC15



- COTS Component for Defense & Avionics Applications
- Environmental Performance to MIL-STD 810
- 10 to 50 VDC Transient Input Range
- 15 to 40 VDC Steady State Input Range
- 15W Max Output Power
- -55°C to 100°C Operation
- Cooling Plates and Mounting Holes for Easy Integration
- Synchronous Rectification on Low Voltage Outputs
- MIL-STD 461E EMI Performance
- Frequency Synchronization

Introduction

The MTC15 is a COTS DC-DC converter developed specifically for the defense and avionics market. This product has a full military specification while offering the short lead-times and cost benefits of a COTS component.

The MTC15 uses a forward converter design switching at 450 kHz giving excellent size, efficiency and EMC performance. The input range is designed to provide short term operation over 10 – 50 VDC to enable the converter to work at full power through the dips and surges commonly seen in vehicle and aircraft applications. A soft start circuit provides well-controlled outputs with no overshoot.

Comprehensive control functions such as voltage trim, remote sense, inhibit and frequency synchronization to an external source are standard features.

When used in conjunction with the MTF input filter module the MTC15 complies to MIL-STD 461E CE/CS MIL-STD 1275A/B/C and MIL-STD 704A.



T H E X P E R T S I N P O W E R

Input Characteristics

Characteristic	Minimum	Typical	Maximum	Units	Notes & Conditions
Input Voltage	15.5	28	40	VDC	Continuous
Transient Input Voltage Range	10		50	VDC	10V for 10 s, 50V for 1 s at full load
UVLO Turn On	13.5		14.8	VDC	
UVLO Turn Off	8.5		9.8	VDC	
Maximum Input Current				A	See models and ratings table for details
Inrush Current		40		A	Peak value
Input Reverse Voltage Protection					External components required

Output Characteristics

Characteristic	Minimum	Typical	Maximum	Units	Notes & Conditions
Output Voltage				VDC	See models and ratings table for details
Output Current				A	See models and ratings table for details
Output Set Tolerance			±100	mV	
Minimum Load	0			A	No minimum load required
Ripple & Noise Vout ≤5V		33.5	60	mV	100% load and 20 MHz BW
Vout >5V			1	%	100% load and 20 MHz BW
Overvoltage Protection ⁽¹⁾	110		120	%	Vout nominal
Overcurrent Protection	105		150	%	At Vin nominal
Overtemperature Protection ⁽¹⁾	102		107	°C	Baseplate temp. with 2°C to 5°C hysteresis
Remote Sense			0.5	V	Total voltage compensation
Load Regulation			±1	%	Vout nominal
Load Step Output Transient			±3	%	Vout nominal 75-25% or 25-75% load changes
Load Step Recovery			500	µs	Within 1% of Vout nom
Line Regulation			±1	%	Vout nominal at 15.5-40 Vin
Line Step Output Transient			±3	%	Vout nominal at 15.5-40 Vin
Line Step Recovery			500	µs	Time for Vout to recover to 1% of Vout nom, with line step 15.5-40 Vin
Maximum Output Capacitance			300 x Iout max	µF	
Start Up Time		35		ms	See fig. 18 to 21

1. Overtemperature and Overvoltage Protection can be removed by factory please contact technical sales for more information.

Models & Ratings

Power	Output Voltage			Output Current	Input Current ⁽²⁾		Efficiency	Model Number
	Nominal	Min ⁽¹⁾	Max ⁽¹⁾		No Load	Full Load		
10 W	3.3 VDC	3.3 VDC	4.0 VDC	3.03 A	0.04 A	0.46 A	77%	MTC1528S3V3
12 W	5 VDC	4.0 VDC	6.0 VDC	2.40 A	0.05 A	0.53 A	81%	MTC1528S05
15 W	12 VDC	9.0 VDC	13.8 VDC	1.25 A	0.04 A	0.67 A	80%	MTC1528S12
15 W	15 VDC	11.0 VDC	17.0 VDC	1.00 A	0.05 A	0.67 A	80%	MTC1528S15
15 W	28 VDC	20.0 VDC	30.0 VDC	0.54 A	0.03 A	0.69 A	78%	MTC1528S28

1. Indicates maximum and minimum voltage adjustment (Maximum includes Remote Sense adjustment).

2. Vin = 28 VDC.

General Specifications

Characteristic	Minimum	Typical	Maximum	Units	Notes & Conditions
Efficiency				%	See models table and performance graphs
Isolation Voltage			1500	VDC	Input to output
			1000	VDC	Input to case
			500	VDC	Output to case
Switching Frequency	400	450	500	kHz	Frequency synch 400-500 kHz. See note
MTBF					Consult technical sales
Inhibit	On = TTL High or open circuit; Off = TTL Low or short circuit				
Rth Case - Ambient	Output Voltage			Rth Case - Ambient	
	3.3 V			17.3 °C/W	
	5 V			17.6 °C/W	
	12 V			16.3 °C/W	
	15 V			16.3 °C/W	
	28 V			15.3 °C/W	

Note. Control signal needs to be TTL 0-5 VDC square wave. The trigger is the falling edge.

Environmental

Characteristic	Minimum	Typical	Maximum	Units	Notes & Conditions
Operating Case Temperature	-40		+100	°C	Baseplate temperature
Operating Ambient Temperature	-40		+85	°C	
Extended Temperature Range	-55		+100	°C	Baseplate temperature. See note.
Storage Temperature	-55		+100	°C	
Humidity			88	%	Relative humidity
Salt Atmosphere			48	Hours	MIL-STD 810E Method 509.1
Altitude			70000	Ft	MIL-STD 810D Method 500.2
Shock			100	g	MIL-STD 810D Method 516.3
Vibration	10		2000	Hz	MIL-STD 810D Method 514.3
Bump			40	g	2000 bumps in each axes MIL-STD 810D Method 516.3

Note. For -55 °C extended operating range, add suffix '-LT' to the part number. e.g. MTC1528S05-LT

Electromagnetic Compatibility

	Standard	Test Level	Criteria	Notes & Conditions
Conducted Emissions	MIL-STD-461E	CE101/CE102		
	DEF-STAN-59-41	TBA		MTF50 module is required
Immunity	MIL-STD-1275A/B/C	Spikes Surges Ripple	±250 V for 100 µs 100 V for 50 ms (see note) 14 VAC pk-pk	MTF50 module is required
	MIL-STD-704A	600 V input transient	10µs 50Ω source impedance	MTF50 module is required
	MIL-STD-704B-F		50 V for 10 ms	
Conducted Susceptibility	MIL-STD-461E	CS101, CS114, CS115, CS116		MTF50 module is recommended

Note. 0.5 Ω source impedance

Safety Approvals

Standard	Category
CE	LVD

Block Diagram





Figure 1. MTC15 Block Diagram

Overcurrent Protection



MTC1528SXX has constant current protection. After reaching the limit between 105% to 150% of I_{out} (current limit point) it will reduce the output voltage protecting the converter from overheating. When V_{out} nom is in the range of 40% to 70% the power will drop to 0 (trip point). The unit will attempt to restart after 700ms typical.

Figure 2. Overcurrent Protection

Remote Sensing




Figure 3. MTC15 - Remote Sense Connection Diagram

Notes.

1. To use the remote sense connect +Sense pin to +Vout.
2. When trim or remote sense are not in use leave Sense pin not connected or connected locally to +Vout.

Voltage Trim




Figure 4. MTC15 - Trim connections




Figure 5. MTC1528S3V3 - Max and Min Adjustment




Figure 6. MTC1528S05 - Max and Min Adjustment




Figure 7. MTC1528S12 - Max and Min Adjustment




Figure 8. MTC1528S15 - Max and Min Adjustment




Figure 9. MTC1528S28 - Max and Min Adjustment

Notes.

1. When adjusting the output voltage do not go above the specified output voltage range (refer to tables) as the Over Voltage Protection may be triggered when fitted.

EMC Performance Curves




Figure 10. MTC1528S05 without a filter




Figure 11. MTC1528S05 with MTF50 filter

EMC Filter Connection Diagram




Figure 12. MTC15 - EMC Filter connection diagram

Parallel Configuration




Figure 13. Parallel configuration suitable for redundant operation

Efficiency




Figure 16. Typical efficiency for MTC1528S05




Figure 17. Typical efficiency for MTC1528S28

Start Up Time




Figure 18. Start up time for MTC1528S05 with full resistive load - 35 ms




Figure 19. Start up time for MTC1528S05 at full load and 790 μ F - 34 ms




Figure 20. Start up time for MTC1528S28 with full resistive load - 32.4 ms





Figure 21. Start up time for MTC1528S28 at full load and 150 μ F - 41.6 ms

Mechanical Details



MTC15 Connections	
Pin	Function
1	No Pin
2	Case
3	No Pin
4	- Vin
5	Synchronisation
6	+ Vin
7	Inhibit
8	No Pin
9	No Pin
10	No Pin
11	+Sense
12	-Vout (COM)
13	Adjust
14	+Vout

Notes.

1. Dimensions are in inches (mm)
2. Tolerance: ±0.02 inches (±0.5 mm)
3. Weight: 0.04 lb (20 g)
4. Materials & Finish:
 - Pin - Material: Cu Zn30 2.5µm Ni
Finish: 0.2-0.5µm AU (HV 170-200)
 - Case - Material: Aluminium (Al Mg Si 0.5)
Finish: Chromated
 - Nameplate - Non-conductive plastic



www.xppower.com

North American Sales Offices

California - Anaheim (714) 712-4504
California - San Diego (760) 597-2100
California - Sunnyvale (408) 732-7777
Colorado (720) 279-2449
Florida (813) 996-0698
Georgia (678) 474-0268
Illinois (630) 980-9890

European Sales Offices

Belgium +33 (0)820 801 401
Denmark 43 42 38 33
France 0820 801 401
Germany 0421 63933-0
Italy 039 2876027

Distributors

Austria 02282 3144 Vitecom
Czech Republic 235 366 129 Vums
Czech Republic 377 824 986 Vienna Trading
Finland 09 2906 1990 Cool Power
Israel 09 7498777 Appletec
Poland 022 8133 145 Vienna Trading

Massachusetts (978) 287-7200
New Jersey (973) 658-8001
Texas (972) 578-1530
Washington (206) 491-3822
British Columbia, Canada (604) 469-8782
Toll Free (800) 253-0490

Netherlands 0049 421 639330
Norway +47 63 94 60 18
Sweden 08 555 367 00
Switzerland 056 448 90 80
United Kingdom 0118 984 5515

Poland 022 817 80 22 Euro Electronica
Portugal 93 263 3354 Venco
Russia +7(495)234 0636 Prosoft
South Africa 011 453 1910 Vepac
Spain 93 263 3354 Venco

North American HQ

XP Power
990 Benecia Avenue
Sunnyvale, CA 94085
Phone : +1 408 732-7777
Fax : +1 408 732-2002
Email : nasales@xppower.com

European HQ

XP Power
Horseshoe Park
Pangbourne
Berkshire, RG8 7JW
Phone : +44 (0)118 984 5515
Fax : +44 (0)118 984 3423
Email : eusales@xppower.com

Asian HQ

XP Power
629 Aljunied Road
#04-08 Cititech Industrial Building
389838
Singapore
Phone : +65 68469368
Fax : +65 67418730
Email : apsales@xppower.com



T H E X P E R T S I N P O W E R